

Electronic Technical Services Inc.

211 Conchas SE Albuquerque, NM 87123 PH 505-888-3923 FAX 505-888-3926 Website: www.etsnm.com

CAT5X4 4 Channel Cabling Adaptor Set

Description

The CAT5X4 adaptor set is used to transmit the audio signal from up to 4 Sound Surveillance microphones (or any other line level sources using on board RCA connectors) down a single standard CAT5 cable. Microphones are powered by an AC adaptor located at the microphone side CAT5X4 adaptor. Compatible with all ETS interface boxes and base stations.



Includes

- 2ea. 4 channel interface box
- 1ea. 12Vdc AC adaptor
- Installation instructions

Wiring requirements:

- 2 conductor shielded to microphones 500' max.
- Max 1000' CAT5 main cable run

Warranty 1 year parts and labor. Made in USA

CAT5x4 Features and Specifications

- RJ45 (8 conductor) female connector block.
- Euro-style connectors for standard interface between the CAT5X4 and all Sound Surveillance microphones.
- RCA or 3.5mm audio inputs and for direct connection to DVRs or other equipment outputs
- Converts our standard unbalanced microphone signals (or any other line level signal) to balanced audio at 600 Ohms impedance permitting the use of CAT5 unshielded cable runs.
- Compatible with all SM1-X series microphones
- Max CAT5 cable run 1000 feet.
- Dimensions: L 4.3 x W 2.7 x H 1.6.